













Ref: 5907489607704

Digital Clamp Meter Habotest HT208A True RMS
Digital Clamp Meter Habotest HT208A True RMS

## Habotest HT208A digital clamp meter

HT208A is a practical device with which you can check the value of various parameters, for example, AC voltage and current, resistance, temperature, inrush current and many others. The product provides accurate measurements, and the results are displayed on the LCD screen. The HT208A also features a flashlight for convenient operation in dark rooms.

## Multifunctional device

You will use the HT208A in many situations. You can check the value of AC voltage, resistance, capacitance, temperature, frequency, NCV, etc. Furthermore, you can also check continuity and true RMS value.

## Safe use

The device is completely safe to use. You can, for example, detect voltage without touching, thanks to the NCV sensors. The meter's jaws, thanks to their maximum width of 40 mm, allow you to make measurements comfortably without damaging the circuit. The flashlight function ensures comfortable and safe work in dark rooms.

## Additional features

When it receives an electromagnetic signal, the NCV sensor will send an audible alarm, and if the voltage or current is high, the LCD

Mobilemax - Gadgets and Accessories Rua Vasco da Gama n61, 8005-411, Estoi - Faro, Portugal (Continente) Phone: +351962484153
(Call to national mobile network)
Email: info@mobilemax.pt



screen color will turn orange. What's more, the device will automatically turn off to save power if no action is performed within 15 min.

**Function** HT208A HT208D DC voltage 6V/60V/600V/1000V  $\pm(1\%+3)$ 6V/60V/600V/1000V  $\pm(1\%+3)$ AC voltage 6V/60V/600V/750V  $\pm(1.2\%+3)$ 6V/60V/600V/750V  $\pm(1.2\%+3)$ DC current n/a  $60A/600A/1000A \pm (2.5\%+5)$ AC current 60A/600A/1000A  $\pm(3.0\%+5)$ 60A/600A/1000A  $\pm(3.0\%+5)$ Resistance  $600\Omega/6k\Omega/60k\Omega/600k\Omega/6M\Omega/60M\Omega$  $\pm(1.0\%+3)$  $600\Omega/6k\Omega/60k\Omega/600k\Omega/6M\Omega/60M\Omega$  $\pm(1.0\%+3)$ Capacity  $10nF/100nF/1\mu F/10\mu F/100\mu F/1mF/10mF \pm (4.0\%+3),$  $100mF \pm (5.0\% + 5)$  $10nF/100nF/1\mu F/10\mu F/100\mu F/1mF/10mF \pm (4.0\% + 3),$  $100mF \pm (5.0\% + 5)$ Frequency 10Hz/100Hz/1kHz/10kHz/100kHz/1MHz/10MHz  $\pm(1.0\%+3)$ 10Hz/100Hz/1kHz/10kHz/100kHz/1MHz/10MHz  $\pm(1.0\%+3)$ Duty 1%~99%  $\pm(1.0\%+2)$ 1%~99%  $\pm(1.0\%+2)$ Temperature -40°C~1000°C

Mobilemax - Gadgets and Accessories Rua Vasco da Gama n61, 8005-411, Estoi - Faro, Portugal (Continente)

±(1.0%+3) -40°C~1000°C

Phone: +351962484153
(Call to national mobile network)
Email: info@mobilemax.pt



Phone: +351962484153

Email: info@mobilemax.pt

(Call to national mobile network)

 $\pm(1.0\%+3)$ Counts 6000 6000 Auto/manual range Yes Yes Continuity Yes, LED and buzz Yes, LED and buzz Diode Yes Yes Data hold Yes Yes NCV Yes, LED and buzz Yes, LED and buzz Double color backlight Yes Yes Flashlight Yes Yes Low battery indicator Yes Yes Auto power off Yes Yes True RMS Yes Yes LPF Yes Yes MAX/MIN Yes Yes V-LoZ No Yes Power 2x AA batteries (in the box) 2x AA batteries (in the box) Weight

about 380 g



about 380 g
Size
240 x 85 x 40 mm
240 x 85 x 40 mm
Size of jaws
44 mm
44 mm
Safety
EN61010-1, -2-030 EN61010-2-033,

EN61326-1 CAT III 1000V, CATIV 600V

EN61010-1, -2-030 EN61010-2-033,

EN61326-1 CAT III 1000V, CATIV 600V

Price:

Before: € 39.9012

Now: € 37.99

Phone: +351962484153

Email: info@mobilemax.pt

(Call to national mobile network)

Tools, Measuring tools, Electric meters